


FORM PTO-1390 (REV 11-2000)	U.S. DEPARTMENT OF COMMERCE PATENT AND TRADEMARK OFFICE	ATTORNEY'S DOCKET NUMBER 1275-49
TRANSMITTAL LETTER TO THE UNITED STATES DESIGNATED/ELECTED OFFICE (DO/EO/US) CONCERNING A FILING UNDER 35 U.S.C. 371		U.S. APPLICATION NO. (If known, see 37 C.F.R. 1.5) 10/070802 <i>Unassigned</i>
INTERNATIONAL APPLICATION NO. PCT/JP00/01523	INTERNATIONAL FILING DATE March 14, 2000	PRIORITY DATE CLAIMED
TITLE OF INVENTION VITERBI DECODER		
APPLICANT(S) FOR DO/EO/US Masahiko KISHINO		

Applicant herewith submits to the United States Designated/Elected Office (DO/EO/US) the following items and other information:

- ☒ This is a **FIRST** submission of items concerning a filing under 35 U.S.C. 371.
- ☐ This is a **SECOND** or **SUBSEQUENT** submission of items concerning a filing under 35 U.S.C. 371.
- ☒ This is an express request to begin national examination procedures (35 U.S.C. 371(f)). The submission must include items (5), (6), (9) and (21) indicated below.
- ☐ The U.S. has been elected by the expiration of 19 months from the priority date (Article 31).
- A copy of the International Application as filed (35 U.S.C. 371(c)(2)).
 - ☐ is attached hereto (required only if not communicated by the International Bureau).
 - ☒ has been communicated by the International Bureau.
 - ☐ is not required, as the application was filed in the United States Receiving Office (RO/US).
- ☒ An English language translation of the International Application as filed (35 U.S.C. 371(c)(2)).
 - ☒ is attached hereto.
 - ☐ has been previously submitted under 35 U.S.C. 154(d)(4).
- ☐ Amendments to the claims of the International Application under PCT Article 19 (35 U.S.C. 371(c)(3)).
 - ☐ are attached hereto (required only if not communicated by the International Bureau).
 - ☐ have been communicated by the International Bureau.
 - ☐ have not been made; however, the time limit for making such amendments has **NOT** expired.
 - ☐ have not been made and will not be made.
- ☐ An English language translation of the amendments to the claims under PCT Article 19 (35 U.S.C. 371(c)(3)).
- ☒ An oath or declaration of the inventor(s) (35 U.S.C. 371(c)(4)).
- ☐ A English language translation of the annexes of the International Preliminary Examination Report under PCT Article 36 (35 U.S.C. 371(c)(5)).

Items 11 To 20 below concern document(s) or information included:

- ☐ An Information Disclosure Statement under 37 C.F.R. 1.97 and 1.98.
- ☒ An assignment document for recording. A separate cover sheet in compliance with 37 C.F.R. 3.28 and 3.31 is included.
- ☒ A **FIRST** preliminary amendment.
- ☐ A **SECOND** or **SUBSEQUENT** preliminary amendment.
- ☐ A substitute specification.
- ☐ A change of power of attorney and/or address letter.
- ☐ A computer-readable form of the sequence listing in accordance with PCT Rule 13ter.2 and 35 U.S.C. 1.821-1.825.
- ☐ A second copy of the published international application under 35 U.S.C. 154(d)(4).
- ☐ A second copy of the English language translation of the international application under 35 U.S.C. 154(d)(4).
- ☒ Other items or information. PTO Form 1449 and Intl Search Report , **PRELIMINARY AMENDMENT**
NR 3-12-02

U.S. APPLICATION NO. (If known, see 37 C.F.R. 1.5) Unassigned 10070802		INTERNATIONAL APPLICATION NO. PCT/JP00/01523		ATTORNEY'S DOCKET NUMBER 1275-49	
21. <input checked="" type="checkbox"/> The following fees are submitted:				CALCULATIONS PTO USE ONLY	
BASIC NATIONAL FEE (37 C.F.R. 1.492(a)(1)-(5)): -- Neither international preliminary examination fee (37 C.F.R. 1.482) nor international search fee (37 C.F.R. 1.445(a)(2)) paid to USPTO and International Search Report not prepared by the EPO or JPO\$1040.00 -- International preliminary examination fee (37 C.F.R. 1.482) not paid to USPTO but International Search Report prepared by the EPO or JPO.....\$890.00 -- International preliminary examination fee (37 C.F.R. 1.482) not paid to USPTO but international search fee (37 C.F.R. 1.445(a)(2)) paid to USPTO\$740.00 -- International preliminary examination fee (37 C.F.R. 1.482) paid to USPTO but all claims did not satisfy provisions of PCT Article 33(1)-(4).....\$710.00 -- International preliminary examination fee (37 C.F.R. 1.482) paid to USPTO and all claims satisfied provisions of PCT Article 33(1)-(4).....\$100.00 <div style="text-align: right;">ENTER APPROPRIATE BASIC FEE AMOUNT =</div>				<div style="text-align: right;">\$ 890.00</div>	
Surcharge of \$130.00 for furnishing the oath or declaration later than <input type="checkbox"/> 20 <input type="checkbox"/> 30 months from the earliest claimed priority date (37 C.F.R. 1.492(e)).				\$ 0.00	
CLAIMS	NUMBER FILED	NUMBER EXTRA	RATE		
Total Claims	3	-20 = 0	X \$18.00	\$ 0.00	
Independent Claims	2	-3 = 0	X \$84.00	\$ 0.00	
MULTIPLE DEPENDENT CLAIMS(S) (if applicable)			\$280.00	\$ 0.00	
TOTAL OF ABOVE CALCULATIONS =				\$ 890.00	
<input type="checkbox"/> Applicant claims small entity status. See 37 CFR 1.27. The fees indicated above are reduced by 1/2.				0.00	
SUBTOTAL =				\$ 890.00	
Processing fee of \$130.00, for furnishing the English Translation later than <input type="checkbox"/> 20 <input type="checkbox"/> 30 months from the earliest claimed priority date (37 C.F.R. 1.492(f)).				0.00	
TOTAL NATIONAL FEE =				\$ 890.00	
Fee for recording the enclosed assignment (37 C.F.R. 1.21(h)). The assignment must be accompanied by an appropriate cover sheet (37 C.F.R. 3.28, 3.31). \$40.00 per property				40.00	
Fee for Petition to Revive Unintentionally Abandoned Application (\$1280.00 - Small Entity = \$640.00)				0.00	
TOTAL FEES ENCLOSED =				\$ 930.00	
				Amount to be: refunded	\$
				Charged	\$
a. <input checked="" type="checkbox"/> A check in the amount of \$930.00 to cover the above fees is enclosed. b. <input type="checkbox"/> Please charge my Deposit Account No. 14-1140 in the amount of \$_____ to cover the above fees. A duplicate copy of this form is enclosed. c. <input checked="" type="checkbox"/> The Commissioner is hereby authorized to charge any additional fees which may be required, or credit any overpayment to Deposit Account No. <u>14-1140</u> . A <u>duplicate</u> copy of this form is enclosed. d. <input checked="" type="checkbox"/> The entire content of the foreign application(s), referred to in this application is/are hereby incorporated by reference in this application.					
NOTE: Where an appropriate time limit under 37 C.F.R. 1.494 or 1.495 has not been met, a petition to revive (37 C.F.R. 1.137(a) or (b)) must be filed and granted to restore the application to pending status.					
SEND ALL CORRESPONDENCE TO: NIXON & VANDERHYE P.C. 1100 North Glebe Road, 8 th Floor Arlington, Virginia 22201-4714 Telephone: (703) 816-4000			<div style="text-align: center;">  SIGNATURE </div> <div style="text-align: center;"> H. Warren Burnam, Jr. NAME </div> <div style="display: flex; justify-content: space-between; margin-top: 20px;"> <div style="text-align: center;"> 29,366 REGISTRATION NUMBER </div> <div style="text-align: center;"> March 12, 2002 Date </div> </div>		

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

In re Patent Application of

Masahiko KISHINO

Atty. Ref.: 1275-49

Serial No. Unassigned

Group: unknown

Filed: March 12, 2002

Examiner: unknown

For: VITERBI DECODER

* * * * *

Assistant Commissioner for Patents
Washington, DC 20231

Sir:

PRELIMINARY AMENDMENT

In order to place the above-identified application in better condition for examination, please amend the application as follows:

IN THE CLAIMS

Please replace the paragraph beginning at page 4, line 2 with the following rewritten paragraph:

In the description hereinbelow, the value presenting the probability of a path is called path metric, and the value presenting the probability for each unit period of reception is called branch metric. The path metric can be translated as a sum of the probabilities of transitions to a certain internal state. The branch metric can be translated as a sum of the probabilities of individual bits at a transition from one internal state to the next internal state.

RECEIVED 031202

REMARKS

The change to the specification replaces a clerical error in the specification.


Attached hereto is a marked-up version of the changes made to the specification by the current amendment. The attached page(s) is captioned "Version With Markings To Show Changes Made."

Respectfully submitted,

NIXON & VANDERHYE P.C.

March 12, 2002

By: _____



H. Warren Burnam, Jr.
Reg. No. 29,366

HWB:lsh
1100 North Glebe Road, 8th Floor
Arlington, VA 22201-4714
Telephone: (703) 816-4000
Facsimile: (703) 816-4100

20020312 091302

VERSION WITH MARKINGS TO SHOW CHANGES MADE

IN THE SPECIFICATION

The paragraph beginning at page 4, line 2 has been rewritten as follows:

In the description hereinbelow, the value presenting the probability of a path is called path metric, and the value presenting the probability for each unit period of reception is called branch metric. The path metric can be translated as a sum of the probabilities of transitions to a certain internal state. The branch metric can be translated as a sum of the probabilities of individual bits at a transition from one [baibu] internal state to the next internal state.

23/pvt

1

DESCRIPTION

VITERBI DECODER

5 Technical Field

The present invention relates to a Viterbi decoder which performs error correction of received convolutional codes.

Background Art

10 Conventionally, the Viterbi decoding technique for performing maximum likelihood decoding of convolutional codes has been known. In this Viterbi decoding technique, since a sequence closest to the received code sequence is selected, based on the Viterbi decoding algorithm, from the code
15 sequences which could be generated on the transmitting side encoder, it is possible to decode the received codes even when they involve errors. In this way, the Viterbi decoding technique has a high correcting capability against random errors arising over the communication path, and in particular,
20 this technique can provide a great coding gain when combined with soft decision decoding. Therefore, Viterbi decoders have been widely adopted to decode error correction codes for mobile communications systems and others.

To begin with, this Viterbi algorithm will be described
25 briefly. Here, consider convolutional codes with a coding

10070802-0312001

rate of $1/2$ and a constraint length $K=3$ which are given by generator polynomials,

$$G1(D) = 1+D^2$$

$$G2(D) = 1+D+D^2$$

5 where 'D' indicates the data delay and '+' indicates addition of one bit only.

Fig.1 is a block diagram showing a configuration of a Viterbi decoder for generating the above convolutional codes. As shown in this figure, this Viterbi decoder is comprised of shift registers, namely registers 101A and 101B, adders 102A, 102B and 102C for performing modulo-two addition. Here, this decoder has four internal states, each given by (b_1, b_2) , explicitly, internal state $(0,0)$, internal state $(0,1)$, internal state $(1,0)$ and internal state $(1,1)$, and each
10 internal state can make a transition to two internal states when an input is given.
15

Specifically, as shown in Fig.2, in the case of internal state $(0,0)$ the decoder makes a transition to internal state $(0,0)$ when the input is 0 and a transition to internal state $(0,1)$ when the input is 1; in the case of internal state $(0,1)$ the decoder makes a transition to internal state $(1,0)$ when the input is 0 and a transition to internal state $(1,1)$ when the input is 1; in the case of the internal state $(1,0)$ the decoder makes a transition to internal state $(0,0)$ when the
20 input is 0 and a transition to internal state $(0,1)$ when the
25

input is 1; and in the case of the internal state (1,1) the decoder makes a transition to internal state (1,0) when the input is 0 and a transition to internal state (1,1) when the input is 1.

5 Fig.3 is a trellis diagram showing the above internal state transitions. In the diagram, the branches represented by solid line indicate transitions when the input is '0' and the branches represented by dashed line indicate transitions when the input is '1'. The numerals attached to each branch are the code symbols (G1, G2) output when the transition of the branch occurs. As seen in this diagram, two paths always merge at each state. In the Viterbi algorithm, the maximum likelihood path is selected from the two paths at each internal state, and when survivor paths up to a predetermined length have been selected, the most probable one is detected from the selected paths at different internal states to thereby decode the received codes.

10

15

The selection of the maximum likelihood path is made based on the probability information of each of the merging paths. In a hard-decision Viterbi algorithm, the Hamming distances between each path bit sequence and the received bit sequence are summed to produce the probability of the path. In a soft-decision Viterbi algorithm, the squares of the Euclidean distances between each path bit sequence and the received bit sequence are summed to produce the probability

20

25

10070802.031202

of the path.

In the description hereinbelow, the value presenting the probability of a path is called path metric, and the value presenting the probability for each unit period of reception is called branch metric. This path metric can be translated as a sum of the probabilities of transitions to a certain internal state. The branch metric can be translated as a sum of the probabilities of individual bits at a transition from one baibu state to the next internal state.

The Euclidean distance between two strings of data, i.e., received data (r_1, r_2) and data (s_1, s_2) generated by a transmission meter is given as expression as follows:

$$\sqrt{(s_1 - r_1)^2 + (s_2 - r_2)^2}$$

In Viterbi decoding, the square of the Euclidean distance is expressed as:

$$(s_1 - r_1)^2 + (s_2 - r_2)^2 = s_1^2 - 2 \times s_1 \times r_1 + r_1^2 + s_2^2 - 2 \times s_2 \times r_2 + r_2^2$$

and data (s_1, s_2) which minimizes the above value of the expression is determined.

Here, since received data (r_1, r_2) is fixed and hence r_1 and r_2 are constant regardless of the values (s_1, s_2) , these can be omitted from the expression. Further, as to the transmitted data (s_1, s_2) , for elements s_1 and s_2 , assuming s_1 or s_2 to be '-1' when the data is '0' and assuming s_1 or s_2 to be '1' when the data is '1', s_1^2 and s_2^2 are constant regardless of the values (s_1, s_2) , so that these can be omitted

10070802-031200

from the expression. Further, when the remaining part is divided by 2, the expression is reduced to $-s_1 \times r_1 - s_2 \times r_2$.

From this expression, if $s_1 = -1$, $-s_1 \times r_1$ is r_1 . Hence if $r_1 = -1$, the term $-s_1 \times r_1$ is reduced to -1 , if $r_1 = 0$, the term is reduced to 0, and if $r_1 = 1$, the term is reduced to 1. If $s_1 = 1$, $-s_1 \times r_1$ is $-r_1$. Hence if $r_1 = -1$, the term is reduced to 1, if $r_1 = 0$, the term is reduced to 0, and if $r_1 = 1$, the term is reduced to -1 .

Accordingly, $-s_1 \times r_1$ results in a value linearly varying from 0 to 2 in accordance with received data r_1 (-1 to 1) if $s_1 = -1$ whereas $-s_1 \times r_1$ results in a value linearly varying from 2 to 0 in accordance with received data r_1 (-1 to 1) if $s_1 = 1$. When the resolution of received data r_1 shown in Fig.4 is set at 3 bits, the metrics shown in Fig.5 can be obtained from the above method.

Next, operations based on soft-decision processing will be described. In contrast to the hard-decision process which uses binary signals '0' and '1', the soft-decision process performs decisions based on multi-levels signals. In soft-decision using eight levels with three bits as shown in Figs.4 and 5, assuming only one bit data, when the information bit is '0', if the received level is '0', the branch metric results in '0' and if the received level is '7', the branch metric results in '7'. When the information bit is '1', if the received level is '0', the branch metric results in '7'

and if the received level is '7', the branch metric results in '0'. It should be noted that the smaller this branch metric value, the more probable the branch is.

Fig.6 is a trellis diagram showing a soft-decision metric processing example. In this soft-decision metric process, suppose that an information sequence is given as '0110000', the code sequence is given as '00', '11', '10', '10', '11', '00' and '00', and the received sequence is given as '2', '4', '3', '6', '7', '2', '7', '5', '5', '7', '1', '0', '1' and '2'. For the transition from the internal state '00' at time instant '0' to the internal state '00' at time instant '1', since the probability for the first bit '0' is '2' and the probability for the second bit '0' is '4', the metric results in $2+4 = 6$. The branch metrics for all the paths can be obtained in the same way. In the diagram, the numeral along each line segment denotes the branch metric and the numeral in hatching located at each internal-state and time-instant point denotes the path metric.

As a result of the calculation, the two paths merging into the internal state '00' at time instant '7' are one from the internal state '00' at time instant '6' and the other from the internal state '10' at time instant '6'. As to the path from the internal state '00' at time instant '6', the path metric at time instant '6'/internal state '00' is '21' and the branch metric from the internal state '00' at time

10070802.031202

instant '6' to the internal state '00' at time instant '7' is '3', so that the probability of the path results in '24'. On the other hand, as to the path from the internal state '10' at time instant '6', the path metric at time instant '6'/internal state '10' is '32' and the branch metric from the internal state '10' at time instant '6' to the internal state '00' at time instant '7' is '11', so that the probability of the path results in '43'. Therefore, '24' is assumed as the path metric at time instant '7'/internal state '00', that is, the path from the internal state '00' at time instant '6' to the internal state '00' at time instant '7' is selected. Here, in the diagram, 'x' denotes the discarded path at the merging point.

As shown in Fig.7, by tracing the survivor path along the arrows or in the reverse direction of the sequence of the received data, the decoded result can be obtained. In Fig.6, the underlined numerals of the received sequence denotes error bits in transmission. As understood from the decoded result, the original information sequence can be obtained even when three bits of errors have occurred.

Fig.8 shows a typical configuration of a Viterbi decoder for decoding convolutional codes based on the Viterbi algorithm, which is comprised of a branch metric calculator 1 for calculating the branch metric between the received sequence and each branch; an ACS portion 2 for selecting the

10070802-0312001

survivor path and calculating the path metric of the survivor path; a path metric memory 3 for storing the path metric value at each internal state; a path memory 4 for storing the estimated output of a selected path; and a backtracing processor 5 for detecting the address of the most probable path metric and performing control of the path memory.

The Viterbi decoder thus configured operates, as shown in the flowchart in Fig.9, in such a manner that it reads the received data and calculates branch metrics and updates the path metric into the path memory (Steps S2 to S5) until one entire frame is completed and when the frame has been completed (Step S1) then it outputs the decoded result by backtracing (Step S6).

For such Viterbi decoders, various techniques have been proposed in order to improve calculation efficiency. As shown in Fig.10, a technique (see Japanese Patent Application Laid-Open Sho 63 No.122323) is disclosed in which a soft-decision data converting circuit A is provided so as to convert the input data in accordance with the circumstances so that it is used for calculations of branch metrics to thereby assign weights to the input bits. Another technique (see Japanese Patent Application Laid-Open Hei 7 No.245567) is disclosed as shown in Fig.11, in which a normalizing circuit (maximum likelihood value subtraction) B is provided to search for the maximum likelihood value from all the branch metrics

and subtract the value from each branch metric so as to narrow the data range to thereby determine the maximum likelihood value in branch metric.

Use of soft-decision of the Viterbi algorithm improves error collection characteristics as the bit precision of input data is enhanced, as seen in the BER characteristic chart in Fig.12. However, enhancement of the bit precision of input data increases the number of bits handled in the internal processor, leading to the problem of system scale enlargement. The same problem occurs with the method of assigning weights on the input bits and with the normalizing method by determining the maximum likelihood value in branch metric.

Illustratively, as shown in the BER characteristic chart in Fig.12, in a case of a Viterbi decoding process with a constraint length of 9 and a coding rate of $1/3$, for example, when the bit accuracy of input data is set at three bits, the data can be correctly processed by an ACS portion having six or more internal operational bits if the process is combined with appropriate normalization. However, when the input bit accuracy is set at four bits, not less than 7 or 8 internal operational bits are needed in the ACS portion even in combination with an appropriate normalization process. The internal operational bit length increases from six bits to 8 bits, the circuit scale also needs to be enlarged proportionally, to as large as a little over 1.3 times.

It is therefore an object of the present invention to provide a Viterbi decoder which is able to improve error correction characteristics while suppressing enlargement of the system scale.

5

Disclosure of Invention

In order to solve the above problem, the present invention is configured as follows.

10

The first aspect of the present invention is a Viterbi decoder comprising: a branch metric calculating portion for calculating a branch metric value based on a received sequence; a bit range converting portion for converting a bit range of the branch metric value calculated by the branch metric calculating portion; a path metric calculating portion for calculating a path metric value based on the branch metric values whose bit range has been converted by the bit range converting portion; and a decoding portion for decoding received codes based on the path metric value calculated by the path metric calculating portion.

15

20

The second aspect of the present invention is, in addition to the Viterbi decoder defined in the first aspect, is characterized in that the bit range converting portion converts the bit range by truncating a least significant bit of the branch metric value calculated by the branch metric calculating portion.

25

10070802-031202

The third aspect of the present invention is a method of Viterbi decoding comprising the steps of: calculating a branch metric value based on a received sequence; calculating a path metric value based on the branch metric values; and decoding received codes based on the path metric value, the method being characterized in that a bit range of the branch metric value is converted and the path metric value is calculated based on the branch metric values whose bit range has been converted.

According to the configurations of the present invention, the following effects can be obtained.

According to the first configuration, the branch metric calculating portion calculates branch metric values based on the received sequence, then the bit range converting portion converts the bit range of the calculated branch metric values into that operable by the path metric calculating portion. The path metric calculating portion calculates the path metric value based on the branch metric values whose bit range has been converted. The decoding portion decodes the received codes based on the calculated path metric value. Thereby, it is possible to improve the bit accuracy of input data without increasing the number of internal operational bits handled in the path metric calculating portion.

According to the second configuration, the branch metric calculating portion calculates branch metric values based

on a received sequence, then the bit range converting portion omit the least significant bit of the calculated branch metric values so as to convert the bit range of them into that operable by the path metric calculating portion. The path metric calculating portion calculates the path metric value based on the branch metric values whose bit range has been converted. The decoding portion decodes the received codes based on the calculated path metric value. Thereby, it is possible to improve the bit accuracy of input data without increasing the number of internal operational bits handled in the path metric calculating portion.

According to the third configuration, branch metric values are calculated based on the received sequence, the bit range of the branch metric values is converted and the path metric value is calculated based on the branch metric values whose bit range has been converted. Then the received codes are decoded based on the path metric value. Thereby, it is possible to improve the bit accuracy of input data without increasing the number of operational bits for calculation of the path metric value.

Brief Description of Drawings

Fig.1 is a block diagram showing a conventional example of a convolutional encoder;

Fig.2 is an illustrative diagram showing internal state

transitions in the same convolutional encoder;

Fig.3 is a trellis diagram showing internal state transitions in the same convolutional encoder;

5 Fig.4 is an illustrative chart showing an example of a soft-decision signal;

Fig.5 is an illustrative chart showing the metrics of information bits with a received bit precision set at 3 bits;

Fig.6 is a trellis diagram showing internal state transitions in a conventional soft-decision process;

10 Fig.7 is an illustrative diagram showing a decoding process in the same trellis diagram;

Fig.8 is a block diagram showing a configuration of a conventional Viterbi decoder;

15 Fig.9 is a flowchart for illustrating the processing sequence of Viterbi decoding in the same Viterbi decoder;

Fig.10 is a block diagram showing an example of branch metric calculation according to a conventional example;

Fig.11 is a block diagram showing another example of branch metric calculation according to a conventional example;

20 Fig.12 is a BER characteristic chart showing the BER characteristic of a conventional example;

Fig.13 is a block diagram showing a configuration of a Viterbi decoder according to one embodiment of the present invention;

25 Fig.14 is a flowchart for illustrating the processing

10070802.031202

sequence of Viterbi decoding in the same Viterbi decoder;

Fig.15 is a trellis diagram showing internal state transitions in a soft-decision process using the same Viterbi decoder;

5 Fig.16 is an illustrative chart showing the metrics of information bits when the received bit precision is set at four bits;

Fig.17 is a trellis diagram when an error occurs in the soft-decision process according to a conventional example;

10 Fig.18 is a BER characteristic chart showing an example of BER characteristics in the same Viterbi decoder;

Fig.19 is a partially enlarged chart of the same BER characteristic chart;

15 Fig.20 is a block diagram showing an example of a specific configuration of a branch metric calculator;

Fig.21 is a block diagram showing an example of a specific configuration of a bit range converter;

Fig.22 is a block diagram showing another example of a specific configuration of a bit range converter;

20 Fig.23 is a block diagram showing an example of a specific configuration of an ACS portion;

Fig.24 is a BER characteristic chart showing another example of BER characteristics in the same Viterbi decoder; and

25 Fig.25 is a partially enlarged chart of the same BER

10070802-031202

characteristic chart.

Best Mode for Carrying Out the Invention

The embodiment of the present invention will hereinbelow
5 be described in detail with reference to the drawings.

Fig.13 is a block diagram showing a configuration of
a Viterbi decoder according to one embodiment of the present
invention. This decoder is comprised of a branch metric
calculator 1 for calculating the metric between the received
10 sequence and each branch, a bit range converter 11 for
converting the bit range of branch metric values calculated
by branch metric calculator 1 so as to be suitable to the
number of calculation bits to be used in an ACS portion 2,
ACS portion 2 for selecting a survivor path and calculating
15 the path metric of the survivor path, a path metric memory
3 for storing the path metric value of each internal state,
a path memory 4 for storing the estimated output of a selected
path; and a backtracing processor 5 for detecting the address
of the most probable path metric and performing control of
20 the path memory.

The Viterbi decoder thus configured operates, as shown
in the flowchart in Fig.14, in such a manner that it reads
the received data and calculates the branch metrics, optimizes
the branch metrics and updates the path metrics and stores
25 them into the path memory (Steps S2 to S5, S11) until one

10070802-031202

frame is completed and when the frame has been completed (Step S1) then it outputs the decoded result by backtracing (Step S6).

To begin with, a Viterbi decoder configured as above with its constraint length set at 3 and coding rate set at 1/2 will be described. The generator polynomials as follows are used:

$$G_0 = 1 + D^2$$

$$G_1 = 1 + D + D^2$$

Fig.15 is a trellis diagram showing a soft-decision metric processing example when the input bit precision is set at '4' in the Viterbi decoder thus configured as above. In this soft-decision metric process, suppose that an information sequence is given as '0110000', the code sequence is given as '00', '11', '10', '10', '11', '00' and '00', and the received sequence is given as '7', '8', '5', '13', '10', '4', '12', '3', '3', '9', '5', '8', '6' and '5'. In this case, for the transition from the internal state '00' at time instant '0' to the internal state '00' at time instant '1', as shown in the metric table in Fig.16, the probability for the first bit '0' is '7' and the probability for the second bit '0' is '8', so that the metric results in '7+8' = '15', or '1111', and then the least significant bit is omitted by bit range converter 11. Therefore, the metric results in '111' or '7'. The branch metrics for all the paths can be calculated in

the same way. In the diagram, the numeral along each line segment denotes the branch metric and the numeral in hatching located at each internal-state and time-instant point denotes its path metric.

5 As a result of the calculation, the two paths merging into the internal state '00' at time instant '7' are one from the internal state '00' at time instant '6' and the other from the internal state '10' at time instant '6'. As to the path from the internal state '00' at time instant '6', the path metric at time instant '6'/internal state '00' is '35' and the branch metric from the internal state '00' at time instant '6' to the internal state '00' at time instant '7' is '5', so that the probability of the path results in '40'. On the other hand, as to the path from the internal state 10 '10' at time instant '6', the path metric at time instant '6'/internal state '10' is '32' and the branch metric from the internal state '10' at time instant '6' to the internal state '00' at time instant '7' is '9', so that the probability of the path results in '41'. Therefore, '40' is assumed as 15 the path metric at time instant '7'/internal state '00', that is, the path from the internal state '00' at time instant '6' to the internal state '00' at time instant '7' is selected. Here, in the diagram, 'x' denotes the discarded path at the 20 merging point.

25 Then, by tracing the survivor path in the reverse

10070802-031200

direction of the sequence of the received data, the decoded result can be obtained. In Fig.15, the underlined numerals of the received sequence denotes error bits in transmission. As understood from this decoded result, the original
 5 information sequence can be obtained even when four bits of errors have occurred.

In contrast, when the same received signal is subjected to the soft-decision metric process with an input bit accuracy of '3' in the Viterbi decoder mentioned in reference to the
 10 prior art, the received sequence is obtained as '3', '4', '2', '6', '5', '2', '6', '1', '1', '4', '2', '4', '3' and '2', as shown in Fig.17. Metric calculation based on this received sequence results as follows. That is, the two paths merging into the internal state '00' at time instant '7',
 15 are one from the internal state '00' at time instant '6' and the other from the internal state '10' at time instant '6'. As to the path from the internal state '00' at time instant '6', the path metric at time instant '6'/internal state '00' is '34' and the branch metric from the internal state '00'
 20 at time instant '6' to the internal state '00' at time instant '7' is '5', so that the probability of the path results in '39'. On the other hand, as to the path from the internal state '10' at time instant '6', the path metric at time instant '6'/internal state '10' is '29' and the branch metric from
 25 the internal state '10' at time instant '6' to the internal

state '00' at time instant '7' is '9', so that the probability of the path results in '38'. Therefore, '38' is assumed as the path metric at time instant '7'/internal state '00', that is, the path from the internal state '10' at time instant '6' to the internal state '00' at time instant '7' is selected. Here, in the diagram, 'x' denotes the discarded path at the merging point.

Then, by tracing the survivor path in the reverse direction of the sequence of the received data, the decoded result can be obtained. However, as understood from this decoded result, when four bits of errors have occurred, a path selection fault occurs from the internal state '10' at time instant '6' to the internal state '00' at time instant '7', hence causes errors in the information sequence, thus making it impossible to obtain the original information sequence.

In this way, according to the present embodiment, it is possible to improve error correction characteristics while keeping the number of operational bits in ACS 3 from exceeding '6'. Fig.18 is a BER characteristic chart showing the bit error ratio (BER) characteristic (with an input bit precision of '4') when the present embodiment is applied, in comparison with the bit error ratio (BER) characteristics (with an input bit precision of '3' and with an input bit precision of '4') of the conventional example. Fig.19 is a partially enlarged

chart of the same chart. As understood from the charts, the embodiment shows some degradation compared to the conventional example wherein full calculation is performed with an input bit precision of '4', but presents some improvement in characteristics compared to the conventional example wherein full calculation is performed with an input bit precision of '3'.

Next, a Viterbi decoder configured as above, with its constraint length set at 9 and coding rate set at 1/3 will be described. The generator polynomials as follows are used:

$$G_0 = 1 + D^2 + D^3 + D^5 + D^6 + D^7 + D^8$$

$$G_1 = 1 + D + D^3 + D^4 + D^7 + D^8$$

$$G_2 = 1 + D + D^2 + D^5 + D^8.$$

Fig.20 is a constructional example of a branch metric calculator 1 in the Viterbi decoder configured as above. This calculator is comprised of a trellis generator 21, selectors 22, 23 and 24 and 6-bit adders 25 and 26.

Trellis generator 21 is adapted to determine from which information bit, '0' or '1', a metric should be determined.

In a calculating example at an internal state '01111000b(=078h)', for input data '0',

$$G_0 = 1+1+1 = 1$$

$$G_1 = 1+1 = 0$$

$$G_2 = 1 = 1.$$

For input data '1',

$$G0 = 1+1+1+1 = 0$$

$$G1 = 1+1+1 = 1$$

$$G2 = 1+1 = 0.$$

When $G0$, $G1$ and $G2$ are '0', selectors 22, 23 and 24 use
 5 respective metrics corresponding to information bit '0' for
 the received levels of data A, B and C. When $G0$, $G1$ and $G2$
 are '1', the selectors use respective metrics corresponding
 to information bit '0' for the received levels of data A,
 B and C. Each output from these selectors 22, 23 and 24 is
 10 supplied to adders 25 and 26, where these are summed to output
 branch metric values $Y1$ and $Y2$.

When the input bit precision is set at three bits, the
 outputs from selectors 22, 23 and 24 range from 0 to 7.
 Therefore, the range of branch metrics is from 0 to 21 (10101b
 15 in binary), and the bit precision needs five bits. When the
 input bit precision is set at four bits, the outputs from
 selectors 22, 23 and 24 range from 0 to 15, so that the range
 of branch metrics is from 0 to 45 (101101b in binary) and
 the bit precision needs six bits.

20 Fig.21 is a constructional example of a bit range
 converter 11 in the Viterbi decoder configured as above. This
 converter is comprised of a least significant bit truncating
 portions 31 and 32. These least significant bit truncating
 portions 31 and 32 are adapted to drop the least significant
 25 bit of branch metric values $Y1$ and $Y2$ output from branch metric

calculator 1, so that the values with their least significant bit truncated are output as branch metric values Y1' and Y2' having a bit length which is operable in ACS portion 2. More specifically, for example, when the input bit precision is set at four bits, the branch metric length is set at six bits taking into account the maximum value of the branch metric. Therefore this bit length is truncated into 5 bits as the number of bits which can be operated in ACS portion 2.

Here, as shown in Fig.22, it is possible to round the branch metric values Y1 and Y2 output from branch metric calculator 1 by adding '1' to each of them through 6-bit adders 33 and 34 and dropping the least significant bit through the least significant bit truncating portions 31 and 32.

Fig.23 is a constructional example of an ACS portion 2 in the Viterbi decoder configured as above. This ACS portion is comprised of 6-bit adders 41 to 44, comparators 45 and 46, selectors 47 and 48. Of these, adder 41 sums data K1 from path metric memory 3 and data Y1' from bit range converter 11 to output pt00, adder 42 sums data K1 from path metric memory 3 and data Y2' from bit range converter 11 to output pt01, adder 43 sums data K2 from path metric memory 3 and data Y2' from bit range converter 11 to output pt10, and adder 42 sums data K2 from path metric memory 3 and data Y1' from bit range converter 11 to output pt11.

Comparator 45 compares pt00 and pt10 and outputs the

result as the path data value to R1. Selector 47, in accordance with the result from comparator 45, selects pt00 if $pt00 \leq pt10$ or selects pt10 if $pt00 > pt10$ to output a new path metric S1. Comparator 46 compares pt01 and pt11 and outputs the result as the path data value to R2. Selector 48, in accordance with the result from comparator 46, selects pt01 if $pt01 \leq pt11$ or selects pt11 if $pt01 > pt11$ to output a new path metric S2. Here, these new path metrics S1 and S2 are stored into path metric memory 3.

When the Viterbi algorithm process is implemented by the above configurational example, the BER characteristic shown in Fig.24 is obtained. Here, Fig.24 shows the graphs for an uncoded case, a case with an input bit precision of 3 bits and operational bit length of 6 bits, a case where the present embodiment is employed with an input bit precision of 4 bits and operational bit length of 6 bits, a case where the present embodiment is not employed with an input bit precision of 4 bits and operational bit length of 6 bits and a case where the present embodiment is not employed with an input bit precision of 4 bits and operational bit length of 8 bits. Fig.25 shows its partially enlarged chart.

As understood from the drawings, the BER characteristic when the present embodiment is employed with an input bit precision of 4 bits or where the branch metric values are converted from 6 bits to 5 bits and internal operations are

processed in 6 bits, is more or less inferior to that when the input bit number is set at 4 bits and a large enough number of operational bits are taken or when the branch metric values are directly used with internal operations processed in 8 bits. However, the characteristic can be improved compared to the case where the input bit precision is set at 3 bits and a large enough number of operational bits are taken or where the circuit scale for internal operations is equivalent to the configuration of the embodiment.

As has been described heretofore, according to the invention described in any one of the first through third aspects, since it is possible to improve the bit accuracy of the input data without increasing the number of operational bits for calculating path metrics, it is possible to improve error correction characteristic while suppressing enlargement in system scale.

Industrial Applicability

As has been described, the invention is suitable for a Viterbi decoder which can improve error correction characteristics while suppressing enlargement in system scale.

CLAIMS

1. A Viterbi decoder comprising:

a branch metric calculating portion for calculating a branch metric value based on a received sequence;

5 a bit range converting portion for converting a bit range of the branch metric value calculated by the branch metric calculating portion;

a path metric calculating portion for calculating a path metric value based on the branch metric values whose bit range
10 has been converted by the bit range converting portion; and

a decoding portion for decoding received codes based on the path metric value calculated by the path metric calculating portion.

15 2. The Viterbi decoder according to Claim 1, wherein the bit range converting portion converts the bit range by truncating a least significant bit of the branch metric value calculated by the branch metric calculating portion.

20 3. A method of Viterbi decoding comprising the steps of: calculating a branch metric value based on a received sequence;

calculating a path metric value based on the branch metric values; and

25 decoding received codes based on the path metric value,

10070802-031202

the method being characterized in that a bit range of the branch metric value is converted and the path metric value is calculated based on the branch metric values whose bit range has been converted.

5

10070802.031202

ABSTRACT

It is an object to provide a Viterbi decoder whereby the error correction characteristic is improved whilst enlargement in system scale is suppressed.


5 For this purpose, a bit range converter(11) for converting the bit range of the branch metric values calculated by a branch metric calculator(1) to meet the number of calculation bits used in an ACS portion(2) is provided between branch metric calculator(1) and ACS portion(2) while the
10 decoder reads the received data and calculates the branch metrics, optimizes the branch metrics and change the path metric and store it into the path memory until the frame is completed and when one frame has been completed then it outputs the decoded result by backtracing.

15

10070802.031202

1/23


FIG. 1



10070802-031202
DATED 2080/007


2/23

FIG. 2




3/23

FIG. 3



10070802-031202

FIG. 4




5/23

FIG. 5

RECEIVED LEVEL (AFTER QUANTIZATION)	0	1	2	3	4	5	6	7
METRIC FOR INFORMATION BIT '0'	0	1	2	3	4	5	6	7
METRIC FOR INFORMATION BIT '1'	7	6	5	4	3	2	1	0


7/23

FIG. 7



8/23


FIG. 8



10070802-031202

9/23

FIG. 9



10070802.031202

10/23

FIG. 10





FIG. 11




FILED " 2080 / OCT 10 08 02 PM '08

11/23


FIG. 12

BIT ERROR RATIO IN VITERBI DECODING (RATE = 1/3, K = 9, N₀ = 744) VITERBI (9).0




12/23

FIG. 13




13/23

FIG. 14



10070802-031202

FIG. 15



15/23


FIG. 16

RECEIVED LEVEL (AFTER QUANTIZATION)	0	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15
METRIC FOR INFORMATION BIT '0'	0	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15
METRIC FOR INFORMATION BIT '1'	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0

DATE: 2020/02/01


16/23

FIG. 17



17/23

FIG. 18



18/23

FIG. 19





FIG. 20



20/23

FIG. 21





FIG. 22



21/23

FIG. 23




FIG. 24





FIG. 25

BIT ERROR RATIO IN VITERBI DECODING (RATE = 1/3, K = 9, N₀ = 744)

VITERBI (9).2



Nixon & Vanderhye P.C. (10/99)
(Domestic Non-Assigned/Foreign)

**RULE 63 (37 C.F.R. 1.63)
DECLARATION AND POWER OF ATTORNEY
FOR PATENT APPLICATION
IN THE UNITED STATES PATENT AND TRADEMARK OFFICE**

As a below named inventor, I hereby declare that my residence, post office address and citizenship are as stated below next to my name, and I believe I am the original, first and sole inventor (if only one name is listed below) or an original, first and joint inventor (if plural names are listed below) of the subject matter which is claimed and for which a patent is sought on the invention entitled:

VITERBI DECODER

the specification of which (check applicable box(es)):

☐ is attached hereto
☐ was filed on _____ as U.S. Application Serial No. _____ (Atty Dkt. No.)
☒ was filed as PCT International application No. PCT/JP00/01523 on March 14, 2000
and (if applicable to U.S. or PCT application) was amended on _____

I hereby state that I have reviewed and understand the contents of the above identified specification, including the claims, as amended by any amendment referred to above. I acknowledge the duty to disclose information which is material to the patentability of this application in accordance with 37 C.F.R. 1.56. I hereby claim foreign priority benefits under 35 U.S.C. 119/365 of any foreign application(s) for patent or inventor's certificate listed below and have also identified below any foreign application for patent or inventor's certificate having a filing date before that of the application on which priority is claimed or, if no priority is claimed, before the filing date of this application:

Priority Foreign Application(s):	Patent Application	Country	Day/Month/Year Filed
Application Number			
<u>Hei 11-21044</u>		<u>Japan</u>	<u>29/January/1999</u>

I hereby claim the benefit under 35 U.S.C. §119(e) of any United States provisional application(s) listed below.

Application Number	Date/Month/Year Filed

I hereby claim the benefit under 35 U.S.C. 120/365 of all prior United States and PCT international applications listed above or below and, insofar as the subject matter of each of the claims of this application is not disclosed in such prior applications in the manner provided by the first paragraph of 35 U.S.C. 112, I acknowledge the duty to disclose material information as defined in 37 C.F.R. 1.56 which occurred between the filing date of the prior applications and the national or PCT international filing date of this application:

Prior U.S./PCT Application(s):	Day/Month/Year Filed	Status: patented pending, abandoned
Application Serial No.		

I hereby declare that all statements made herein of my own knowledge are true and that all statements made on information and belief are believed to be true; and further that these statements were made with the knowledge that willful false statements and the like so made are punishable by fine or imprisonment, or both, under Section 1001 of Title 18 of the United States Code and that such willful false statements may jeopardize the validity of the application or any patent issued thereon. And on behalf of the owner(s) hereof, I hereby appoint NIXON & VANDERHYE P.C., 1100 North Glebe Rd., 8th Floor, Arlington, VA 22201-4714, telephone number (703) 816-4000 (to whom all communications are to be directed), and the following attorneys thereof (of the same address) individually and collectively owner's/owners' attorneys to prosecute this application and to transact all business in the Patent and Trademark Office connected therewith and with the resulting patent: I also authorize Nixon & Vanderhye to delete any attorney names/numbers no longer with the firm and to act and rely solely on instructions directly communicated from the person, assignee, attorney, firm, or other organization sending instructions to Nixon & Vanderhye on behalf of the owner(s).

1. Inventor's Signature: Masahiko Kishino Date: Feb. 27, 2002
Inventor: Masahiko KISHINO Japan
(first) MI (last) (citizenship)
Residence: (city) Higashihiroshima-shi (state/country) Hiroshima, Japan
Post Office Address: 4-21-MYN801, Saijoshowa-machi, Higashihiroshima-shi, Hiroshima,
Japan
(Zip Code) 739-0014

2. Inventor's Signature: _____ Date: _____
Inventor: _____
(first) MI (last) (citizenship)
Residence: (city) _____ (state/country) _____
Post Office Address: _____
(Zip Code) _____

FOR ADDITIONAL INVENTORS, check box ☐ and attach sheet with same information and signature and date for each.